
HP 34401A Multimeter

Uncompromising performance for benchtop and system testing

- Measure up to 1000 volts with 6 1/2 digits resolution
 - dc accuracy of 0.0015%
 - ac accuracy of 0.06%
 - 3Hz to 300kHz ac bandwidth
 - 1000 readings/sec. direct to HP-IB
-

Superior performance

The HP 34401A multimeter gives you the performance you need for fast, accurate bench and systems testing. The HP 34401A provides a combination of resolution, accuracy and speed that rivals DMMs costing many times more. A 6 1/2-digit display, 0.0015% Basic 24-hr dcV accuracy and 1,000 readings/sec direct to HP-IB assure you of results that are accurate, fast, and repeatable.

Use it on your benchtop

The HP 34401A was designed with your bench needs in mind. Functions commonly associated with pure bench operation, like continuity and diode test, are built in. A Null feature allows you to remove lead resistance or other fixed offsets in your measurements. Other capabilities like min/max/avg readouts and direct dB and dBm measurements make checkout with your DMM faster and easier.

When you want to store readings for future reference, the HP 34401A gives you the ability to store up to 512 readings in internal memory. For troubleshooting, a reading hold feature lets you concentrate on placing your test leads without having to constantly glance at the display.

Use it for systems testing

For systems use, the HP 34401A gives you faster bus throughput than any other DMM in its class. The HP 34401A can send up to 1,000 readings/sec directly across HP-IB in user-friendly ASCII format.

You also get both HP-IB and RS-232 interfaces as standard features. Voltmeter Complete and External Trigger signals are provided so you can synchronize to other instruments in your test system. In addition, a TTL output indicates Pass/Fail results when limit testing is used.

To ensure both forward and backward compatibility, the HP 34401A includes three command languages (SCPI, HP 3478A and Fluke 8840A /42A), so you don't have to rewrite your existing test software. An optional rack mount kit is available.

Easy to use

To save you time and trouble, all major functions, like selecting the function, range and number of digits, can be accessed on the front panel with one push of a button.



Advanced features are available using menu functions that let you optimize the HP 34401A for your applications.

To further increase your productivity, the HP 34401A can be used in conjunction with HP 34812A BenchLink Meter software. The Windows-based program lets you configure and initiate measurements from your computer, and transfer results from your test instrument to your PC. It even enables direct temperature measurements with the HP 34401A and an RTD or thermistor probe. HP BenchLink Meter also lets you create graphs, charts and histograms to help you evaluate results.

3-year warranty

With your HP 34401A, you get full documentation, a high-quality test lead set, calibration certificate with test data, and a 3-year warranty, all for one low price.

Accuracy Specifications ± (% of reading + % of range)^[1]

Function	Range ^[3]	Frequency, etc.	24 Hour ^[2] 23°C ± 1°C	90 Day 23°C ± 5°C	1 Year 23°C ± 5°C	Temperature Coefficient 0°C – 18°C 28°C – 55°C
dc Voltage	100.0000 mV		0.0030 + 0.0030	0.0040 + 0.0035	0.0050 + 0.0035	0.0005 + 0.0005
	1.000000 V		0.0020 + 0.0006	0.0030 + 0.0007	0.0040 + 0.0007	0.0005 + 0.0001
	10.00000 V		0.0015 + 0.0004	0.0020 + 0.0005	0.0035 + 0.0005	0.0005 + 0.0001
	100.0000 V		0.0020 + 0.0006	0.0035 + 0.0006	0.0045 + 0.0006	0.0005 + 0.0001
	1000.000 V		0.0020 + 0.0006	0.0035 + 0.0010	0.0045 + 0.0010	0.0005 + 0.0001
True rms ac Voltage ^[4]	100.0000 mV	3 Hz - 5 Hz	1.00 + 0.03	1.00 + 0.04	1.00 + 0.04	0.100 + 0.004
		5 Hz - 10 Hz	0.35 + 0.03	0.35 + 0.04	0.35 + 0.04	0.035 + 0.004
		10 Hz - 20 kHz	0.04 + 0.03	0.05 + 0.04	0.06 + 0.04	0.005 + 0.004
		20 kHz - 50 kHz	0.10 + 0.05	0.11 + 0.05	0.12 + 0.04	0.011 + 0.005
		50 kHz - 100 kHz	0.55 + 0.08	0.60 + 0.08	0.60 + 0.08	0.060 + 0.008
		100 kHz - 300 kHz ^[6]	4.00 + 0.50	4.00 + 0.50	4.00 + 0.50	0.20 + 0.02
	1.000000 V to 750.000 V	3 Hz - 5 Hz	1.00 + 0.02	1.00 + 0.03	1.00 + 0.03	0.100 + 0.003
		5 Hz - 10 Hz	0.35 + 0.02	0.35 + 0.03	0.35 + 0.03	0.035 + 0.003
		10 Hz - 20 kHz	0.04 + 0.02	0.05 + 0.03	0.06 + 0.03	0.005 + 0.003
		20 kHz - 50 kHz	0.10 + 0.04	0.11 + 0.05	0.12 + 0.05	0.011 + 0.005
		50 kHz - 100 kHz ^[5]	0.55 + 0.08	0.60 + 0.08	0.60 + 0.08	0.060 + 0.008
		100 kHz - 300 kHz ^[6]	4.00 + 0.50	4.00 + 0.50	4.00 + 0.50	0.20 + 0.02
	100.0000 Ω to 100.0000 MΩ	1 mA Current Source	0.0030 + 0.0030	0.008 + 0.004	0.010 + 0.004	0.0006 + 0.0005
		1 mA	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.0006 + 0.0001
		100 μA	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.0006 + 0.0001
		10 μA	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.0006 + 0.0001
		5.0 μA	0.002 + 0.001	0.008 + 0.001	0.010 + 0.001	0.0010 + 0.0002
		500 nA 10 MΩ	0.015 + 0.001	0.020 + 0.001	0.040 + 0.001	0.0030 + 0.0004
dc Current	10.00000 mA	<0.1 V Burden Voltage	0.005 + 0.010	0.030 + 0.020	0.050 + 0.020	0.002 + 0.0020
	100.0000 mA	<0.6 V	0.010 + 0.004	0.030 + 0.005	0.050 + 0.005	0.002 + 0.0005
	1.000000 A	<1 V	0.050 + 0.006	0.080 + 0.010	0.100 + 0.010	0.005 + 0.0010
	3.00000 A	<2 V	0.100 + 0.020	0.120 + 0.020	0.120 + 0.020	0.005 + 0.0020
True rms ac Current ^[4]	1.000000 A	3 Hz - 5 Hz	1.00 + 0.04	1.00 + 0.04	1.00 + 0.04	0.100 + 0.006
		5 Hz - 10 Hz	0.30 + 0.04	0.30 + 0.04	0.30 + 0.04	0.035 + 0.006
		10 Hz - 5 kHz	0.10 + 0.04	0.10 + 0.04	0.10 + 0.04	0.015 + 0.006
	3.00000 A	3 Hz - 5 Hz	1.10 + 0.06	1.10 + 0.06	1.10 + 0.06	0.100 + 0.006
		5 Hz - 10 Hz	0.35 + 0.06	0.35 + 0.06	0.35 + 0.06	0.035 + 0.006
		10 Hz - 5 kHz	0.15 + 0.06	0.15 + 0.06	0.15 + 0.06	0.015 + 0.006
Frequency or Period ^[8]	100 mV to 750 V	3 Hz - 5 Hz	0.10	0.10	0.10	0.005
		5 Hz - 10 Hz	0.05	0.05	0.05	0.005
		10 Hz - 40 Hz	0.03	0.03	0.03	0.001
		40 Hz - 300 kHz	0.006	0.01	0.01	0.001
Continuity	1000.0 Ω	1 mA Test Current	0.002 + 0.010	0.008 + 0.020	0.010 + 0.020	0.001 + 0.002
Diode Test	1.0000 V	1 mA Test Current	0.002 + 0.010	0.008 + 0.020	0.010 + 0.020	0.001 + 0.002

[1] Specifications are for 1 hr warm-up and 6½ digits, Slow ac filter.

[2] Relative to calibration standards.

[3] 20% over range on all ranges except 1000 Vdc and 750 Vac ranges.



[4] For sinewave input > 5% of range. For inputs from 1% to 5% of range and < 50 kHz, add 0.1% of range additional error.

[5] 750 V range limited to 100 kHz or 8 x 10⁷ Volt-Hz.

[6] Typically 30% of reading error at 1 MHz.

[7] Specifications are for 4-wire ohms function or 2-wire ohms using Math Null. Without Math Null, add 0.2 Ω additional error in 2-wire ohms function.

[8] Input > 100 mV. For 10 mV inputs multiply % of reading error x10.



Measurement Characteristics

dc Voltage	
Measurement Method	Continuously Integrating Multi-slope III A-D Converter
A-D Linearity	0.0002% of reading + 0.0001 % of range
Input Resistance	
0.1V, 1V, 10 V ranges	Selectable 10 M Ω or >10,000 M Ω
100 V, 1000 V ranges	10 M Ω \pm 1%
Input Bias Current	< 30pA at 25° C
Input Protection	1000 V all ranges
dcV:dcV Ratio Accuracy	V_{input} Accuracy + $V_{\text{reference}}$ Accuracy
True rms ac Voltage	
Measurement Method	ac coupled True rms – measures the ac component of the input with up to 400 Vdc of bias on any range.
Crest Factor	Maximum of 5:1 at Full Scale
Additional Crest Factor Errors (non-sinewave)	
Crest Factor 1–2	0.05 % of reading
Crest Factor 2–3	0.15 % of reading
Crest Factor 3–4	0.30 % of reading
Crest Factor 4–5	0.40 % of reading
Input Impedance	1 M Ω \pm 2% in parallel with 100 pF
Input Protection	750Vrms all ranges
Resistance	
Measurement Method	Selectable 4-wire or 2-wire Ohms. Current source referenced to LO input.
Maximum Lead Resistance (4-wire)	10% of range per lead for 100 Ω and 1k Ω ranges. 1k Ω per lead on all other ranges.
Input Protection	1000 V all ranges
dc Current	
Shunt Resistance	5 Ω for 10 mA, 100 mA; 0.1 Ω for 1 A, 3 A.
Input Protection	Externally accessible 3 A 250 V Fuse Internal 7 A 250 V Fuse
True rms ac Current	
Measurement Method	Direct coupled to the fuse and shunt. ac coupled True rms measurement (measures the ac component only).
Shunt Resistance	0.1 Ω for 1 A and 3 A ranges
Input Protection	Externally accessible 3 A 250 V Fuse Internal 7 A 250 V Fuse
Frequency and Period	
Measurement Method	Reciprocal counting technique
Voltage Ranges	Same as ac Voltage Function
Gate Time	1 s, 100 ms, or 10 ms.
Continuity / Diode	
Response Time	300 samples/s with audible tone
Continuity Threshold	Selectable from 1 Ω to 1000 Ω
Measurement Noise Rejection 60 (50) Hz^[1]	
dc CMRR	140 dB
ac CMRR	70 dB
Integration Time	
100 plc / 1.67 s (2 s)	Normal Mode Rejection ^[2] 60 dB ^[3]
10 plc / 167 ms (200 ms)	60 dB ^[3]
1 plc / 16.7 ms (20 ms)	60 dB
<1 plc / 3 ms or 800 μ s	0 dB

Operating Characteristics^[4]

Function	Digits	Readings/s	
dcV, dcI, and Resistance	6 1/2	0.6 (0.5)	
	6 1/2	6 (5)	
	5 1/2	60 (50)	
	5 1/2	300	
	4 1/2	1000	
acV, acI	6 1/2	0.15	Slow (3 Hz)
	6 1/2	1	Medium (20 Hz)
	6 1/2	10	Fast (200 Hz)
	6 1/2	50 ^[5]	
Frequency or Period	6 1/2	1	
	5 1/2	9.8	
	4 1/2	80	
System Speeds [6]			
Configuration Rates		26/s to 50/s	
Autorange Rate (dc Volts)		> 30/s	
ASCII readings to RS-232		55/s	
ASCII readings to HP-IB		1000/s	
Maximum Internal Trig. Rate		1000/s	
Max. Ext. Trig. Rate to Memory		1000/s	
Triggering and Memory			
Reading HOLD Sensitivity		10%, 1%, 0.1%, or 0.01% of range	
Samples/ trigger		1 to 50,000	
Trigger Delay		0 to 3600 s: 10 µs step size	
External Trigger Delay		< 1 ms	
External Trigger Jitter		< 500 µs	
Memory		512 readings	
Math Functions			
NULL, Min/Max/Average, dBm, dB, Limit Test (with TTL output)			
Standard Programming Languages			
SCPI (IEEE-488.2), HP 3478A, Fluke 8840A/42A			
Accessories Included			
Test Lead Kit with probe, alligator, and grabber attachments.			
Operating Manual, Service Manual, test report, and power cord.			
General Specifications			
Power Supply	100 V/120 V/220 V/240 V ±10%		
Power Line Frequency	45 Hz to 66 Hz and 360 Hz to 440 Hz Automatically sensed at power-on.		
Power Consumption	25 VA peak (10W average)		
Operating Environment	Full accuracy for 0° C to 55° C Full accuracy to 80% R.H. at 30° C		
Storage Environment	– 40° C to 75° C		
Weight	3 kg (6.5 lbs)		
Safety	Designed to CSA, UL-1244, IEC-348		
RFI and ESD	MIL-461C, FTZ 1046, FCC		
Vibration and Shock	MIL-T-28800E, Type III, Class 5 (Sine Only)		
Warranty	3 years		

^[1] For 1 k Ω unbalance in LO lead.

^[2] For power line frequency \pm 0.1%.

^[3] For power line frequency \pm 1% use 40 dB or \pm 3% use 30 dB.

^[4] Reading speeds for 60 Hz and (50 Hz) operation.

^[5] Maximum useful limit with default settling delays defeated.

^[6] Speeds are for 4 1/2 digits, Delay 0, Auto-zero and Display OFF.

Ordering Information

HP 34401A Multimeter

Accessories included

Test Lead Kit with probe, alligator, and grabber attachments, operating manual, service manual, calibration certificate, test report, and power cord.

Options

Opt. 908 Rack Mount Kit* (P/N 5062-3972)

Opt. 910 Extra manual set (English)

Opt. OBO DMM without manuals

Opt. W50 Additional 2-year warranty (5-year total)

Opt. 1BP MIL-STD-45662A calibration with data

Manual options (please specify one)

ABA US English

ABD German

ABE Spanish

ABF French

ABJ Japanese

ABZ Italian

ABO Taiwan Chinese

AB1 Korean

Accessories

HP 11059A Kelvin Probe set

HP 11060A Surface Mount Device (SMD) test probes

HP 11062A Kelvin clip set

HP 34130 Deluxe test lead set

HP 34161A accessory pouch

HP 34300A 40 kV ac/dc high voltage probe

HP 34301A 700 MHz RF probe

HP 34302A Clamp-on ac/dc current probe (100 A)

HP 34330A 30 A current shunt

HP 34812A BenchLink Meter software

HP E2308A 5K thermistor probe

* For racking two side-by-side, order both items below

Lock link kit (P/N 5061-9694)

Flange kit (P/N 5062-3974)

HP BenchLink is a trademark of Hewlett-Packard Company.
Windows is a trademark of Microsoft Corporation.

For more information on Hewlett-Packard Test and Measurement products, applications or services please call your local Hewlett-Packard sales offices. One of the following HP centers can help you contact your local HP representative.

United States:

Hewlett-Packard Company
Test and Measurement Organization
5301 Stevens Creek Blvd.
Bldg. 51L-SC
Santa Clara, CA 95052-8059
1 800 452 4844

Canada:

Hewlett-Packard Canada Ltd.
5150 Spectrum Way
Mississauga, Ontario
L4W 5G1
(905) 206 4725

Europe:

Hewlett-Packard
European Marketing Centre
P.O. Box 999
1180 AZ Amstelveen
The Netherlands

Japan:

Yokogawa-Hewlett-Packard Ltd.
Measurement Assistance Center
9-1, Takakura-Cho, Hachioji-Shi
Tokyo 192, Japan
(81) 426 48 3860

Latin America:

Hewlett-Packard
Latin American Region Headquarters
5200 Blue Lagoon Drive, 9th Floor
Maimi, FL 33126 U.S.A.
(305) 267 4245/4220

Australia / New Zealand:

Hewlett-Packard Australia Ltd.
31-41 Joseph Street, Blackburn
Victoria 3130, Australia
131 347 Ext. 2902

Asia Pacific:

Hewlett-Packard Asia Pacific Ltd.
17-21/F Shell Tower, Time Square
1 Matheson Street, Causeway Bay
Hong Kong
(852) 2599 7070

***Within Budget.
Without Compromise.***

Technical information in this document
is subject to change without notice.

Printed in the U.S.A.

Copyright © 1995
Hewlett-Packard Company

5964-0145 EN