



Single-Output: 500 W GPIB



6651A-6655A

Increase test throughput with fast up and down programming time

Protect valuable assemblies with fast protection features

Proven reliability

Low ripple and noise

This series of 500 W linear-regulated dc power supplies is designed to maximize the throughput of DUTs through the manufacturing test process with fast up and down programming time.

Valuable assemblies can be destroyed by a minor component failure that causes a surge of current to flow into the DUT. Fast protection features, including fast crowbar, mode crossover protection, and the ability to connect the protection circuitry of multiple power supplies can increase production yield.

Programming of the dc output and the protection features can be done either from the front panel or using industry standard SCPI commands, via the GPIB. Using the serial link, up to 16 power supplies can be connected through one GPIB address. Test system integration can be further simplified by using the *VXIPlug&Play* drivers. The output voltage and current can also be controlled with analog signals. This is helpful for certain types of noisy environments, and also immediate reactions to process changes.

Lab bench use is enhanced by the fan speed control, which helps to minimize the acoustic noise.

Specifications

(at 0° to 55° C unless otherwise specified)

	6651A	6652A	6653A	6654A	6655A	6651A-J01 Special Order Option
Number of outputs	1	1	1	1	1	1
GPIB	Yes	Yes	Yes	Yes	Yes	Yes
Output ratings						
Output voltage	0 to 8 V	0 to 20 V	0 to 35 V	0 to 60 V	0 to 120 V	10 V
Output current (40° C)	0 to 50 A	0 to 25 A	0 to 15 A	0 to 9 A	0 to 4 A	50 A
Maximum current (50° C/55° C)	45 A/42.5 A	22.5 A/21.3 A	13.5 A/12.8 A	8.1 A/7.7 A	3.6 A/3.4 A	45 A/42.5 A
Programming accuracy at 25° C ±5° C						
Voltage	0.06% + 5 mV	10 mV	15 mV	26 mV	51 mV	6 mV
Current	0.15% + 60 mA	25 mA	13 mA	8 mA	4 mA	60 mA
Ripple and noise						
from 20 Hz to 20 MHz						
Voltage rms	300 µV	300 µV	400 µV	500 µV	700 µV	300 µV
peak-peak	3 mV	3 mV	4 mV	5 mV	7 mV	3 mV
Current rms	25 mA	10 mA	5 mA	3 mA	2 mA	25 mA
Readback accuracy at 25° C ±5° C (percent of reading plus fixed) System models only						
Voltage	0.07% + 6 mV	15 mV	25 mV	40 mV	80 mV	7.5 mV
+Current	0.15% + 67 mA	26 mA	15 mA	7 mA	3 mA	67 mA
–Current	0.35% + 100 mA	44 mA	24 mA	15 mA	7 mA	100 mA
Load regulation						
Voltage	1 mV	2 mV	3 mV	4 mV	5 mV	1 mV
Current	2 mA	1 mA	0.5 mA	0.5 mA	0.5 mA	2 mA
Line regulation						
Voltage	0.5 mV	0.5 mV	1 mV	1 mV	2 mV	0.5 mV
Current	2 mA	1 mA	0.75 mA	0.5 mA	0.5 mA	2 mA
Transient response time	Less than 100 µs for the output voltage to recover to its previous level (within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater) following any step change in load current of up to 50% of rated current					

Supplemental Characteristics

(Non-warranted characteristics determined by design and useful in applying the product)

Average resolution						
Voltage	2 mV	5 mV	10 mV	15 mV	30 mV	2.5 mV
Current	15 mA	7 mA	4 mA	2.5 mA	1.25 mA	15 mA
OVP	12 mV	30 mV	54 mV	93 mV	190 mV	16 mV
OVP accuracy	160 mV	400 mV	700 mV	1.2 V	2.4 V	200 mV



Single-Output: 500 W GPIB (Continued)

Supplemental Characteristics for all model numbers

dc Floating Voltage: Output terminals can be floated up to ± 240 Vdc from chassis ground

Remote Sensing: Up to half the rated output voltage can be dropped in each load lead. The drop in the load leads subtracts from the voltage available for the load.

Command Processing Time: Average time required for the output voltage to begin to change following receipt of digital data is 20 ms for the power supplies connected directly to the GPIB

Output Programming Response Time: The rise and fall time (10/90% and 90/10%) of the output voltage is less than 15 ms. The output voltage change settles within 1 LSB (0.025% x rated voltage) of final value in less than 60 ms.

Down Programming: An active down programmer sinks approximately 20% of the rated output current

Modulation: (Analog programming of output voltage and current)

Input signal: 0 to -5 V

Input impedance: 10 k Ohm nominal

ac Input: (ac input frequency 47 to 63 Hz)

Voltage 100 Vac 120 Vac 220 Vac 240 Vac

Current 12 A 10 A 5.7 A 5.3 A

Input Power: 1,380 VA, 1,100 W at full load; 120 W at no load

GPIB Interface Capabilities: SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT1, E1, and C0. IEEE-488.2 and SCPI-compatible command set.

Regulatory Compliance: Listed to UL 1244; conforms to IEC 61010-1.

Size: 425.5 mm W x 132.6 mm H x 497.8 mm D (16.75 in x 5.22 in x 19.6 in)
See page 101 for more details

Weight: Net, 25 kg (54 lb); shipping, 28 kg (61 lb)

Warranty Period: One year

Specifications

(at 0° to 55°C unless otherwise specified)

	6651A-J03 Special Order Option	6651A-J09 Special Order Option	6652A-J03 Special Order Option	6653A-J04 Special Order Option	6653A-J17 Special Order Option
Number of outputs	1	1	1	1	1
GPIB	Yes	Yes	Yes	Yes	Yes
Output ratings					
Output voltage	6 V	17V/20 V	27 V	40 V	30 V
Output current (40°C)	60 A	30 A/15 A	18.5 A	12.5 A	17.5 A
Maximum current (50°C/55°C)	54 A/51 A	27 A/25.5 A 13.5 A/12.75 A	16.65 A/15.72 A	11.25 A/10.6 A	15.75 A/14.87 A
Programming accuracy at 25°C $\pm 5^\circ\text{C}$					
Voltage 0.06% +	5 mV	10 mV	13.5 mV	17.5 mV	15 mV
Current 0.15% +	75 mA	36 mA	25 mA	13 mA	16 mA
Ripple and noise					
from 20 Hz to 20 MHz					
Voltage rms	300 μV	300 μV	450 μV	1.6 mV	400 μV
peak-peak	3 mV	4 mV	4.5 mV	5 mV	4 mV
Current rms	30 mA	13 mA	10 mA	5 mA	6 mA
Readback accuracy at 25°C $\pm 5^\circ\text{C}$ (percent of reading plus fixed) System models only					
Voltage 0.07% +	6 mV	15 mV	20.5 mV	30 mV	25 mV
+Current 0.15% +	80 mA	40 mA	26 mA	15 mA	18 mA
-Current 0.35% +	150 mA	55 mA	44 mA	24 mA	28 mA
Load regulation					
Voltage	1 mV	2 mV	2 mV	3.5 mV	3 mV
Current	6.5 mA	2 mA	1 mA	1 mA	0.5 mA
Line regulation					
Voltage	0.5 mV	0.5 mV	0.5 mV	1 mV	1 mV
Current	2 mA	2 mA	2 mA	0.75 mA	0.75 mA
Transient response time	Less than 100 μs for the output voltage to recover to its previous level (within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater) following any step change in load current of up to 50% of rated current				

Supplemental Characteristics

(Non-warranted characteristics determined by design and useful in applying the product)

Average resolution					
Voltage	2 mV	5 mV	6.75 mV	12 mV	10 mV
Current	18 mA	9 mA	7 mA	4 mA	5 mA
OVP	12 mV	30 mV	30 mV	65 mV	54 mV
OVP accuracy	160 mV	500 mV	400 mV	750 mV	700 mV



Single-Output: 500 W GPIB (Continued)

Ordering Information

Opt 100 87 to 106 Vac, 47 to 63 Hz

Opt 120 104 to 127 Vac, 47 to 63 Hz

Opt 220 191 to 233 Vac, 47 to 63 Hz

Opt 240 209 to 250 Vac, 47 to 63 Hz

* **Opt 908** Rack-mount Kit
(p/n 5062-3977)

* **Opt 909** Rack-mount Kit
w/ Handles (p/n 5063-9221)

Opt 0L2 Extra Standard
Documentation Package

Opt 0B3 Service Manual

Opt 0B0 No documentation package

* Support rails required

Accessories

p/n 1494-0059 Accessory Slide Kit

p/n 1252-3698 7-pin Analog Plug

p/n 1252-1488 4-pin Digital Plug

p/n 5080-2148 Serial Link
Cable 2 m (6.6 ft)

E3663AC Support rails for
Agilent rack cabinets

Specifications

(at 0° to 55° C unless
otherwise specified)

**6654A-
J04**
Special Order
Option

**6654A-
J05**
Special Order
Option

**6654A-
J12**
Special Order
Option

**6655A-
J05**
Special Order
Option

**6655A-
J10**
Special Order
Option

Number of outputs

1

1

1

1

1

GPIB

Yes

Yes

Yes

Yes

Yes

Output ratings

Output voltage

70 V

50 V

80 V

150 V

156 V

Output current (40° C)

7.5 A

10 A

6 A

3.2 A

3 A

Maximum current (50° C/55° C)

6.75 A/6.37 A

9 A/8.5 A

5.4 A/5.1 A

2.88 A/2.72 A

2.7 A/2.55 A

Programming accuracy at 25° C ±5° C

Voltage

0.06% +

30 mV

26 mV

35 mV

64 mV

71 mV

Current

0.15% +

7 mA

9 mA

7 mA

3.5 mA

4 mA

Ripple and noise

from 20 Hz to 20 MHz

Voltage rms

600 µV

500 µV

700 µV

800 µV

900 µV

peak-peak

6 mV

5 mV

7 mV

8 mV

8 mV

Current rms

5 mA

4 mA

3 mA

2 mA

3 mA

Readback accuracy at 25° C ±5° C

(percent of reading plus fixed)

System models only

Voltage

0.07% +

50 mV

40 mV

58 mV

100 mV

110 mV

+Current

0.15% +

6 mA

8 mA

6 mA

2.5 mA

3 mA

–Current

0.35% +

13 mA

17 mA

16 mA

6.5 mA

7.5 mA

Load regulation

Voltage

4 mV

4 mV

4 mV

6 mV

7 mV

Current

0.5 mA

0.5 mA

0.5 mA

0.5 mA

1 mA

Line regulation

Voltage

1 mV

1 mV

4.5 mV

2 mV

2 mV

Current

0.5 mA

0.5 mA

0.5 mA

0.5 mA

1 mA

Transient response time

Less than 100 µs for the output voltage to recover to its previous level
(within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater)
following any step change in load current of up to 50% of rated current

Supplemental Characteristics

(Non-warranted characteristics determined by design and
useful in applying the product)

Average resolution

Voltage

17.5 mV

15 mV

20 mV

37.5 mV

39.5 mV

Current

1.9 mA

2.75 mA

1.7 mA

8 mA

8 mA

OVP

110 mV

93 mV

130 mV

240 mV

250 mV

OVP accuracy

1.4 V

1.2 V

1.6 V

3 V

3.3 V

Your Requested Excerpt from the Agilent Power Products Catalog

The preceding page(s) are an excerpt from the *2002-2003 Power Products Catalog*. We hope that these pages supply the information that you currently need.

If you would like to have further information about the extensive selection of Agilent dc power supplies, ac sources, and dc electronic loads, please visit www.agilent.com/find/power to print a copy of the complete Power Products catalog, or to request that a copy be sent to you. You will also find a lot of other useful information on this web site.

In the full Power Products Catalog, you will find that Agilent offers much more than basic power generation. If you need basic, clean, power for your lab bench, it's there. But in each product category, we've also integrated the capabilities that you need for a complete power solution, including extensive measurement and analysis capabilities.

Please give us a call at your local Agilent Technologies sales office, or call a regional office listed below, for assistance in choosing or using Agilent power products.

Keep up to date with Agilent's Test and Measurement Email Updates

As an Email Update subscriber, you will receive periodic customized email updates that match the areas of interest that you have specified. Your update will include products and services, applications and support information, events, and promotions. Sign up today at www.agilent.com/find/emailupdates. Check off dc power supplies, ac power sources or electronic loads on your registration form, and we will promptly let you know what's new in power products! Our Privacy Statement at www.agilent.com/go/privacy describes our commitment to you regarding your privacy.

To see a copy of the user's guide, please visit our Web site at www.agilent.com/find/manuals

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:
www.agilent.com/find/assist

Phone or Fax

United States:
(tel) 1 800 829 4444

Canada:
(tel) 1 877 894 4414
(fax) (905) 282-6495

China:
(tel) 800-810-0189
(fax) 1-0800-650-0121

Europe:
(tel) (31 20) 547 2323
(fax) (31 20) 547 2390

Japan:
(tel) (81) 426 56 7832
(fax) (81) 426 56 7840

Korea:
(tel) (82-2) 2004-5004
(fax) (82-2) 2004-5115

Latin America:
(tel) (305) 269 7500
(fax) (305) 269 7599

Taiwan:
(tel) 080-004-7866
(fax) (886-2) 2545-6723

Other Asia Pacific Countries:
(tel) (65) 375-8100
(fax) (65) 836-0252
Email: tm_asia@agilent.com

Product specifications and descriptions in this document subject to change without notice.



Agilent Technologies